

**Wichita State University
Computing and
Telecommunications Services
Telephone Service Users Guide**

Please refer to this guide for instructions on your 7400, 8400 or 6400 series digital telephone.

For questions regarding the use of an 8110 telephone see the accompanying users guide. For questions regarding Voice Mail call the Interim Director of Telecommunications John Rankin at extn. 3535. For all other questions regarding your telephone service call Telecommunications at 978-3535.

Using Softkeys

If your telephone has a display, it may have a series of eight or more buttons directly below the display. These buttons are softkey buttons and give you access to certain features assigned to those buttons. You can activate available softkey features by pressing

Menu

and then the softkey below the feature abbreviation. If the feature you want to use is not on the bottom line of the display press

Next

or

Prev

until you see the feature you wish to access. When the feature is active an arrow appears above the feature.

Autodial (AD)

To program/reprogram an AD button.

1. Pick up handset. Note: For speakerphone users, press a call appearance button or press

Speaker

Conference

To add another party to a call (for a total of up to 6 parties).

1. While on the line with the first party (do not press hold) press

Conference

2. Dial number of new party and wait for answer.

3. Again, press **Conference**

4. Repeat steps 1 through 3 for additional conference connections.

To add a call you have put on hold to another call to which you are connected.

1. Press **Conference**

2. Press call appearance of call on hold (first call).

3. Again, press **Conference**

Drop

Allows user to disconnect the last party added to a conference call.

Exit/ Normal (display feature)

When you are ready to leave a Display or Softkey Mode and return to Normal Display Mode press **Normal or **Exit****

Hold

To put a call on hold press

Hold

To answer a new call while active on another.

Send All Calls

To send all calls to coverage (usually voice mail).

Note: Can be done while on the phone.

1. While on-hook, press softkey below **SAC**, an arrow will light above the symbol (for softkey users) **Send All Calls**
Or Press **Send All Calls**
>Green light will come on next to button.
Or Dial Send All Calls access code ***3**.

To cancel Send All Calls

1. While on-hook, press softkey below **SAC**, arrow will go out (for softkey users)
Or Press **Send All Calls**
>Green light will go out.
Or Dial Send All Calls access code **#3**.

View Button (display feature)

To view the feature stored on a call appearance/ feature button Or the last number you dialed Or a number stored on an autodial button (where applicable)

1. Press the softkey below **View**
Or Press **View**
2. Press the selected feature or autodial or redial button or last number dialed.
> Feature assignment on a button or telephone number is shown on the display.
3. See Exit/Normal section for instructions on how to exit this special display mode.

2. Press softkey below Prog

Or Press **Program**

Or Dial AD Program access code *0.

3. Press AD button to be programmed.

4. Dial outside number, extension, or feature access code you want to store (up to 24 digits).

5. Press the AD button to be programmed again or press #.

6. Repeat Steps 3 through 5 to program additional buttons.

7. Hang up.

To place an AD call press selected AD button.

Button View (display feature)

To view a number stored on an Autodial button.

1. Press **Btn Vu**

2. Press the Autodial button and telephone number is shown on the display.

3. See Exit/ Normal section for instructions on how to exit this special display mode.

Automatic Call Back

To automatically place another call to an extension that was busy or did not answer.

1. During a call attempt, press softkey below **AutCB** or Dial Auto Call Back access code *5.

2. Hang up. Note: You hear a 3-burst

1. Press **Hold**

2. Press call appearance of incoming call.

To return to held call press call appearance of held call.

Inspect (display feature)

When a call comes into a display phone, information about the call is shown on the phones display. If a second call comes in while on line with the first the information about the second call is displayed for 30 seconds. If you missed this information or if you want to see information on a line placed on hold then press

Inspect

See *Exit/Normal* section for instructions on how to exit this display mode.

Reset Speakerphone

Note: You can use this feature only if the Reset Spkr label or symbol appears under the **Speaker** button.

If your Speaker button light is flashing or to adjust the speakerphone to the surrounding room acoustics.

1. While on-hook, press

Shift/ Select and then press the

Speaker button.

> You will hear a series of tones.

Reset Speakerphone

To temporarily redirect all calls to an extension or outside number.

1. Press softkey below **Cfrwd** (for softkey users)

Test

To test the lights and display (if applicable) on your telephone.

1. Press and hold down **Test**

(you may have to press

Shift/ Select first)

> Green Test light goes on.

> Button lights go on in two separate groups, and, if your terminal has a display, all display segments fill in.

2. To end test, release **Test**

Time/Date (display feature)

To see time and date.

1. Press softkey below **TmDay**.

Or Press **Time/Date**

> Display will return to normal in 5 seconds.

Transfer

To send present call to another extension on campus or within your office.

1. Press **Transfer**

2. Dial number where call is to be transferred.

3. If you would like to announce the transfer you can wait for second party to answer, make the announcement then press

Transfer

again and the two parties will be connected.

priority ring when both you and the called extension are idle, you may then pickup handset to place second call.

To Cancel Automatic Call back press the Autocall back button again or dial cancel code #5.

Call Pickup

To answer a call placed to a member of your pickup group, usually a phone within earshot.

1. Press softkey below CPkUp

Or Press **Call Pickup**

Or Dial Call Pickup access code #4.

Or Press **Call Forward**

Or Dial Call Forward access code *2.

2. Dial extension or number where calls will be sent.

3. Hang up.

To cancel Call Forwarding.

1. While on-hook, press softkey below Cfrwd (for softkey users)

Or Press **Cancel Call Forward**

Or Dial Call Forward cancel code #2.

If you would prefer not to announce the transfer, then press

Transfer

and the two parties will be connected.

4. Hang up.

Call Park

To park a call at your extension (for retrieval at any extension).

You may press softkey below **CPark** (for softkey users),

Or Press **Call Park**

Then hang up.

Or do this:

1. Press Transfer

2. Dial the Call Park access code *6.

3. Dial the extension where call is to be parked.

4. Press Transfer again and then hang up.

To retrieve a parked call from any extension.

1. Dial the Answer Back access code #6.

2. Dial the extension where the call is parked.